

# Diesel Generator Set

# **mtu** 12V2000 DS825

# 380V - 415V/50 Hz/standby power/NOx emission optimized 12V2000G76F/air charge air cooling



Optional equipment and finishing shown. Standard may vary.

# Product highlights

#### **Benefits**

- Low fuel consumption
- Optimized system integration ability
- High reliability and availability of power
- Long maintenance intervals
- Optimized ratio between size and power
- Wide operating range without derating

### Suppor

- Global product support offered

### Standards

- Engine-generator set is designed and manufactured in facilities certified to standards ISO 2008:9001 and ISO 2004:14001
- Generator set complies to G3 according to ISO 8528
- Generator meets NEMA MG1, BS5000, ISO, DIN EN and IEC standards
- NFPA 110

### Power rating

- System rating: 825 kVA
- Accepts rated load in one step per NFPA 110
- Generator set complies to G3 according to ISO 8528-5
- Generator set exceeds load steps according to ISO 8528-5

### Performance assurance certification (PAC)

- Engine-generator set tested to ISO 8528-5 for transient response
- 85% load factor for continuous power applications
- Verified product design, quality and performance integrity
- All engine systems are prototype and factory tested

### Complete range of accessories available

- Control panel
- Power panel
- Fuel system
- Fuel connections with shut-off valve mounted to base frame
- Starting/charging system
- Exhaust system
- Mechanical radiator
- Oversized voltage alternators

### Emissions

- NOx emission optimized
- Tier 2 and NEA (ORDE) optimization optionally available

### Certifications

- CE certification option
- VDE4110 certification



# Application data 1)

	Emis	sion optimized <sup>2</sup>	Emission	optimized <sup>2</sup>
Engine			Combustion air requirements	
Manufacturer		mtu	Combustion air volume: m³/s	0.9
Model		12V2000G76F	Max. air intake restriction: mbar	40
Type		4-cycle		
Arrangement		12V	Cooling/radiator system	
Displacement: I		26.8	Coolant flow rate (HT circuit): m³/hr	31.6
Bore: mm		135	Heat rejection to coolant: kW	300
Stroke: mm		156	Heat rejection to charge air: kW	160
Compression ratio		17.5	Heat radiated to ambient: kW	35
Rated speed: rpm		1500	Fan power for mech. radiator (40°C): kWm	34
Engine governor		ADEC (ECU 9)	Fan power for mech. radiator (50°C): kWm	51.1
Speed regulation		± 0.25%	Air flow required for mech. radiator	
Max power: kWm		732	(40°C) cooled unit: m <sup>3</sup> /min	969
Mean effective pressure: bar		21.9	Air flow required for mech. radiator	
Air cleaner		dry	(50°C) cooled unit: m³/min	1328
			Engine coolant capacity (without cooling equipment): l	63
Fuel system			Radiator coolant capacity (40°C): I	59
Maximum fuel lift: m		5	Radiator coolant capacity (50°C): l	140
Total fuel flow: I/min		30	Max. coolant temperature (warning): °C	102
			Max. coolant temperature (shutdown): °C	105
Fuel consumption 3)	l/hr	g/kwh		
At 100% of power rating:	175	198	Exhaust system	
At 75% of power rating:	133	201	Exhaust gas temp. (after turbocharger): °C	535
At 50% of power rating:	93	211	Exhaust gas volume: m³/s	2.43
			Maximum allowable back pressure: mbar	50
Lube oil system			Minimum allowable back pressure: mbar	30
Total oil system capacity: l		80		
Max. lube oil temperature (alarm): °C		103	Generator	
Max. lube oil temperature (shutdown): °C		105	Protection class	IP23
Min. lube oil pressure (alarm): bar		4.5	Insulation class	Н
Min. lube oil pressure (shutdown): bar		4	Voltage regulation (steady state)	± 0.25%
			Rado interference class	N

All data refers only to the engine and is based on ISO standard conditions (25°C and 100m above sea level).

<sup>2</sup> Emission optimized data refer to NOx emission optimized and NEA (ORDE) optimized/Tier 2 compliant engines.

<sup>3</sup> Values referenced are in accordance with ISO 3046-1. Conversion calculated with fuel density of 0.83 g/ml. All fuel consumption values refer to rated engine power.

# Standard and optional features

### System ratings (kW/kVA)

Generator model	Voltage	with mechanical radiator**		
		kWel	kVA*	AMPS
Leroy Somer LSA 49.3 L9 (Low voltage Leroy Somer standard)	380 V	660	825	1253
	400 V	660	825	1191
	415 V	660	825	1148
Leroy Somer LSA 50.2 M6 (Low voltage Leroy Somer oversized)	380 V	660	825	1253
	400 V	660	825	1191
	415 V	660	825	1148
Marathon 575RSL7181 (Low voltage Marathon standard)	380 V	660	825	1253
	400 V	660	825	1191
	415 V	660	825	1148
Marathon 740RSL7183 (Low voltage Marathon oversized)	380 V	660	825	1253
	400 V	660	825	1191
	415 V	660	825	1148

<sup>\*</sup> cos phi = 0.8

Electrical outputs may vary depending on generator voltage and ambient conditions. For power outputs consult your *mtu* dealer.

Intake air depression/mbar: 15mbar

Exhaust back pressure/mbar: 30mbar

### **Engine**

- 4-cycle
- Standard single stage air filter
- Oil drain extension & shut-off valve
- Closed crankcase ventilation
- Governor-electronic isochronous ADEC/ECU9
- Dry exhaust manifold
- Electric starting motor (24V)
- NOx emission optimized engine
- $\hfill\Box$  Tier 2 optimized engine
- □ NEA (ORDE) optimized engine

# Generator

- Leroy Somer low voltage generator
- Meets NEMA MG1, BS5000, IEC 60034-1,
   VDE 0530, DIN EN 12601, AS1359
   and ISO 8528 requirements
- Superior voltage waveform
- Solid state, volts-per-Hertz regulator
- 4 pole three-phase synchronous generator
- Brushless, self-excited, self-regulating, self-ventilated
- Digital voltage regulator
- Anti condensation heater

- Stator winding Y-connected, accessible neutral (brought out)
- Protection IP 23
- less than 5% harmonic distorsion
- 2/3 pitch stator windings
- No load to full load regulation
- ± 0.25% voltage regulation no load to full load
- Insulation class H, utilization acc. to H
- Radio suppression EN55011, group 1, cl. B
- Short circuit capability 3xln for 10sec

- Sustained short circuit current of up to 300% of the rated current for up to 10 seconds (Leroy Somer generator)
- Winding and bearing RTDs (without monitoring)
- Excitation by AREP + PMI
- Mounting of CT's: 3x 2 core CT's
- Voltage setpoint adjustment ±10V
- ☐ Sustained short circuit current of up to 250% of the rated current for up to 10 seconds (Marathon generator)
- $\hfill \square$  Marathon low voltage generator
- ☐ Oversized generator


<sup>\*\*</sup> BE, fuel optimized: max. power available up to: open power unit 40°C/400m; NOx emission optimized, EPA Tier 2 compl., NEA: standard operating conditions/open power unit 25°C/100m


# Standard and optional features

Cooling system			
■ Jacket water pump ■ Thermostat(s)	<ul><li>Air charge air cooling</li><li>Mechanical radiator</li></ul>	☐ Jacket water heater	
Control panel			
■ Pre-wired control cabinet for easy application of customized controller (V1+)  ☐ Island operation (V2)  ☐ Automatic mains failure operation with ATS (V3a)  ☐ Automatic mains failure operation incl. control of generator and mains breaker (V3b)  ☐ Island parallel operation of multiple gensets (V4)  ☐ Automatic mains failure operation with short (< 10s) mains parallel overlap synchronization (V5)  ☐ Mains parallel operation of a single genset (V6)	<ul> <li>Mains parallel operation of multiple gensets (V7)</li> <li>Basler controller</li> <li>Deif controller</li> <li>Complete system metering</li> <li>Digital metering</li> <li>Engine parameters</li> <li>Generator protection functions</li> <li>Engine protection</li> <li>SAE J1939 engine ECU communications</li> <li>Parametrization software</li> <li>Multilingual capability</li> <li>Multiple programmable contact inputs</li> <li>Multiple contact outputs</li> <li>Event recording</li> </ul>	<ul> <li>■ IP 54 front panel rating with integrated gasket</li> <li>□ Different expansion modules</li> <li>□ Remote annunciator</li> <li>□ Daytank control</li> <li>□ Generator winding- and bearing temperature monitoring</li> <li>□ Differential protection with multi-function protection relay</li> <li>□ Modbus TCP-IP</li> </ul>	
Power panel			
☐ Available in 600x600 ☐ Phase monitoring relay 230V/400V	<ul><li>☐ Supply for battery charger</li><li>☐ Supply for jacket water heater</li></ul>	☐ Plug socket cabinet for 230V compatible Euro	
Fuel system			
Flexible fuel connectors mounted to base frame	<ul><li>Fuel filter with water separator</li><li>Switchable fuel filter with water separator</li></ul>	☐ Fuel cooler	
Starting/charging system			
■ 24V starter	<ul> <li>Starter batteries, cables, rack, disconnect switch</li> </ul>	<ul><li>□ Battery charger</li><li>□ Redundant starter 2x 7.5kW</li></ul>	
Mounting system			
■ Welded base frame	Resilient engine and generator mounting	■ Modular base frame design	
Exhaust system			
<ul> <li>Exhaust bellows with connection flange</li> <li>Exhaust silencer with</li> <li>10 dB(A) sound attenuation</li> </ul>	aust silencer with 30 dB(A) sound attenuation		

- Represents standard features
- ☐ Represents optional features

# Weights and dimensions





Drawing above for illustration purposes only, based on a standard open power 400 Volt engine-generator set. Lengths may vary with other voltages. Do not use for installation design. See website for unit specific template drawings.

System	Dimensions (LxWxH)	Weight (dry/less tank)
Open power unit (OPU)	4120 x 1910 x 2190 mm	5800 kg

Weights and dimensions are based on open power units and are estimates only. Consult the factory for accurate weights and dimensions for your specific engine-generator set.

### Sound data

- Consult your local *mtu* distributor for sound data.

### **Emissions data**

- Consult your local mtu distributor for emissions data.

# Rating definitions and conditions

- Standby power apply to installations served by a reliable utility source. The standby rating is applicable to varying loads for the duration of a power outage. No overload capability for this rating. Ratings are in accordance with ISO 8528-1, ISO-3046-1, BS 5514 and AS 2789.
- Average load factor: ≤ 85%. Operating hours/year: max. 500.
- Consult your local *mtu* distributor for derating information.